



## FEATURES

- \* 1Hz ~ 120MHz Range
- \* 8 Digit Display (0.3" LED)
- \* 15mVrms High Sensitivity
- \* 5PPM High Stability Time Base
- \* Frequency and Period Measurement
- \* Low Pass Filter Function
- \* Over-Flow Indicator

## GFC-8010H (120MHz)

### SPECIFICATIONS

#### DISPLAY GATE TIME ACCURACY

8 Digit with Hz, kHz, MHz, S, mS,  $\mu$ S, nS and overflow  
 0.1S, 1S, 10 S switch selectable  
 $\pm(1 \text{ Digit} + \text{Time base accuracy})$

#### INPUT

**Sensitivity** 10Hz ~ 10MHz < 15mVrms  
 10MHz ~ 40MHz < 20mVrms  
 40MHz ~ 80MHz < 35mVrms  
 80MHz ~ 120MHz < 50mVrms

**Impedance** 1M $\Omega$ /35pF

**Coupling System** AC Coupling

**Max Input Voltage** 150Vrms

#### TIME BASE

**Oscillation Frequency** 10MHz

**Aging Rate**  $\pm 1$  PPM per month

**Temp. Stability** 25°C  $\pm 5$ °C :  $\pm 5$ PPM

#### RESOLUTION

The maximum resolution is 1 $\mu$ Hz for 10Hz and 0.1Hz for 100MHz  
 Input respectively for frequency measurement and 1nS for 10Hz and  
 0.1 x 10<sup>-15</sup> for 100MHz

#### POWER SOURCE

AC 100V/120V/220V/230V  $\pm 10\%$ , 50/60Hz

#### ACCESSORIES

Instruction Manual x 1  
 Power cord x 1  
 Test Lead GTL-101 x 1

#### DIMENSIONS & WEIGHT

230(W) x 95(H) x 280(D) mm, Approx. 1.7kg

### ORDERING INFORMATION

**GFC-8010** 120MHz Digital Frequency Counter

## Strumenti di Misura Nuovi e Ricondizionati



web. [www.test.it](http://www.test.it)  
 email. [testinst@tin.it](mailto:testinst@tin.it)

Strada Vicinale Battifoglia Z.I.  
 06132 S. Andrea delle Fratte  
 Perugia

(39) 075 87 88 003 tel.  
 (39) 075 87 88 013 fax.  
 (39) 388 85 86 991 vendite  
 (39) 389 48 28 200 vendite  
 (39) 335 61 58 054 direzione