

# Multi-Output D.C. Power Supply

C1

Patent No: ZL 02 3 35264 . 7



## FEATURES

- \* 2, 3 and 4 Independent Isolated Output
- \* Four "3 Digits" LED Displays
- \* 0.01% Load and Line Regulation
- \* Low Ripple and Noise
- \* Tracking Operation and Auto Series/Parallel Operation
- \* Output ON/OFF Switch
- \* Output Voltage and Current Setting When Output Disable
- \* Fan Speed Control Circuit to Minimize Fan Noise
- \* Over Load and Reverse Polarity Protection
- \* Optional European Jack Type Terminal

## GPS-2303/3303/4251/4303

		SPECIFICATIONS												
OUTPUT MODE	Voltage Current Tracking Series Voltage Tracking Parallel Current	GPS-4303				GPS-4251				GPS-3303		GPS-2303		
		CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH4	CH1	CH2	CH3	CH1	CH2
		0 ~ 30V	2.2 ~ 5.2V	8 ~ 15V	0 ~ 25V	3 ~ 6V	8 ~ 15V	0 ~ 30V	5V Fixed	0 ~ 30V			0 ~ 30V	
		0 ~ 3A	1A Max.	1A Max.	0 ~ 0.5A	2.5A Max.	1A Max.	0 ~ 3A	3A Max.	0 ~ 3A			0 ~ 3A	
		0 ~ 60V		----	0 ~ 50V		----	0 ~ 60V		----			0 ~ 60V	
		0 ~ 6A			0 ~ 1A			0 ~ 6A					0 ~ 6A	
CONSTANT VOLTAGE OPERATION (CH1, CH2)	Line Regulation Load Regulation  Ripple & Noise Recovery Time	$\leq 0.01\% + 3mV$ $\leq 0.01\% + 3mV$ (rating current $\leq 3A$ ) $\leq 0.02\% + 5mV$ (rating current $> 3A$ ) $\leq 1mV_{rms}$ , 5Hz ~ 1MHz $\leq 100\mu S$ (50% Load change, Minimum load 0.5A)												
CONSTANT CURRENT OPERATION (CH1, CH2)	Line Regulation Load Regulation Ripple & Noise	$\leq 0.2\% + 3mA$ $\leq 0.2\% + 3mA$ $\leq 3mArms$												
TRACKING OPERATION (CH1, CH2)	Tracking Error Series Regulation Load Regulation Ripple & Noise	$\leq 0.5\% + 10mV$ of the CH1 $\leq 300mV$ $\leq 0.01\% + 3mV$ $\leq 2mV_{rms}$ , 5Hz ~ 1MHz												
GPS-4303 2.2V ~ 5.2V OUTPUT (CH3) GPS-3303 5V FIX OUTPUT (CH3) GPS-4251 3V~6V OUTPUT(CH3)	Line Regulation Load Regulation Ripple & Noise Current Output	$\leq 5mV$ $\leq 15mV$ $\leq 2mV_{rms}$ , 5Hz ~ 1MHz GPS-4303: 1A, GPS-3303: 3A, GPS-4251: 2.5A												
GPS-4303 8V ~ 15V OUTPUT (CH4) GPS-4251 8V~15V OUTPUT (CH4)	Line Regulation Load Regulation Ripple & Noise Current Output	$\leq 5mV$ $\leq 10mV$ $\leq 2mV_{rms}$ , 5Hz ~ 1MHz 1A												
METER	Digital	3 digits 0.5" LED display GPS-4303/4251/3303 Out ON Accuracy $\pm (0.5\% rdg + 2 \text{ digits})$ GPS-4303/4251/3303 Out OFF Accuracy $\pm (0.5\% rdg + 8 \text{ digits})$ GPS-2303 Accuracy $\pm (0.5\% rdg + 2 \text{ digits})$												
INSULATION	Chassis and Terminal Chassis and AC Cord	$\geq DC 500V / 20M\Omega$ $\geq DC 500V / 30M\Omega$												
POWER SOURCE		AC 100V/120V/220V( $\pm 10\%$ )/230V( $+10\% \sim -6\%$ ), 50/60Hz												
ACCESSORIES		Instruction manual x 1, Power cord x 1, GPS-4303: Test lead GTL-104 x 2, GTL-105 x 2; European test lead GTL-203 x 2, GTL-204 x 2 GPS-4251: Test lead GTL-105 x 4; European test lead GTL-203 x 4 GPS-3303: Test lead GTL-104 x 2, GTL-105 x 1; European test lead GTL-203 x 1, GTL-204 x 2 GPS-2303: Test lead GTL-104 x 2; European test lead GTL-204 x 2												
DIMENSIONS & WEIGHT		255(W) x 145(H) x 265(D) mm, Approx. 7 kg (GPS-4303/3303/2303); Approx. 6.3kg (GPS-4251)												

Patent: ZL 02 3 35264.7

## ORDERING INFORMATION

- GPS-4303** 4-channels, 200W D.C. Power Supply
- GPS-4251** 4-channels, 55W D.C. Power Supply
- GPS-3303** 3-channels, 195W D.C. Power Supply
- GPS-2303** 2-channels, 180W D.C. Power Supply

Strumenti di Misura Nuovi e Ricondizionati



Strada Vicinale Battifoglia Z.I.  
06132 S. Andrea delle Fratte  
Perugia

(39) 075 87 88 003 tel.  
(39) 075 87 88 013 fax.  
(39) 388 85 86 991 vendite  
(39) 389 48 28 200 vendite  
(39) 335 61 58 054 direzione

web. www.test.it  
email. testinst@tin.it