



GPM-8212

SPECIFICATIONS	
VOLTAGE	
Range	5V, 10V, 20V, 40V, 80V, 160V, 320V, 640V total 8 ranges by auto-range or manual.
Measurement Type	True rms
Input Resistance	$\geq 1M \Omega$
Maximum Input Voltage	1000V(peak), 700V(rms)
PT Ratio Setting	1 ~ 9999
Accuracy (at 23°C ± 5°C) (Sinewave)	± 0.1% of reading ± 0.1% of range
CURRENT	
Range	160mA, 320mA, 640mA, 1.280A, 2.560A, 5.120A, 10.24A, 20.48A total 8 ranges by auto-range or manual
Measurement Type	True rms
Input Resistance	0.01 Ω
Maximum Input Current	30A(peak), 20A(rms)
CT Ratio Setting	1 ~ 9999
Accuracy (at 23°C ± 5°C) (Sinewave)	± 0.1% of reading ± 0.1% of range
WATT	
Measurement Range	0.32mW ~ 13.10kW
Measurement Type	True rms
Accuracy (at 23°C ± 5°C) (Sinewave)	± 0.2% of reading ± 0.2% of range
POWER FACTOR	
Range	0.001 ~ 1.000
Computation	$W \div (V \times A) = \text{Power factor (PF)}$
FREQUENCY	
Measurement Range	40Hz ~ 400Hz
Accuracy(23°C ± 5°C)	± 0.2% of reading ± 2 digits
GENERAL	
Display	4 digits 0.56" LED and 2 sets of 4 digits 0.4" LED
Minimum Input	2% of range
Response Time	2 cycles/sec
Overload Indicating	" O.L "
POWER SOURCE	
AC 100 ~ 230V, 50/60Hz	
ACCESSORIES	
Instruction manual x 1 , Power cord x 1	
DIMENSIONS & WEIGHT	
251(W) x 91(H) x 291(D) mm, Approx. 1.6kg	

FEATURES

- * Simultaneous Display of W, A, V (PF or Hz)
- * True RMS V, A, W
- * Auto Calibration Via Computer
- * Max. / Min. / Hold Function
- * High Immunity to External Noise
- * CT Ratio (1 ~ 9999)
- * PT Ratio (1 ~ 9999)
- * Option : RS-232C or RS-485 Interface

ORDERING INFORMATION

GPM-8212 A.C. Power Meter

Option

- Opt.01** RS-232C Interface (Factory Installed)
- Opt.02** RS-485 Interface (Factory Installed)

Strumenti di Misura Nuovi e Ricondizionati



Strada Vicinale Battifoglia Z.I.
06132 S. Andrea delle Fratte
Perugia

(39) 075 87 88 003 tel.
(39) 075 87 88 013 fax.
(39) 388 85 86 991 vendite
(39) 389 48 28 200 vendite
(39) 335 61 58 054 direzione

web. www.test.it
email. testinst@tin.it