



IDEAL NETWORKS

LanXPLOER



LanXPLOER Software Release Notes Brief

Summary:

Release v2.0.42 replaces the previous production release (v2.0.23) for previous version of **LanXPLOER** and **LanXPLOER Plus** and production release (v2.0.40) for previous versions of **LanXPLOER Pro**.

Main changes for LanXPLOER series:

- New functionality for v2.0.23 basic and plus model
 - Replace test report format xml to PDF and CSV (summary only)
 - Support wireless report transfer via IDEAL AnyWARE

- Bug fixes
 - Battery capacity indication improved (v2.0.23)
 - Support USB memory key up to 16GB (v2.0.23)
 - Content empty of report after transferring into USB memory key
 - The start-up screen will show original model (basic, Plus or Pro) after upgrading from v2.0.40 to v.2.0.42 to correct the error of showing all models as **LanXPLOER Pro** on the start-up screen
 - Existing test Wi-Fi interface will not conflict with USB Wi-Fi adapter during test report wireless transfer (2.0.40).

Note:

For details please refer to full release notes of LanXPLOER via IDEAL Networks' sales representatives.

LanXPLOER Software Update Instruction

CATION:

All saved data will be erased after upgrading. Please make sure all your data is backed up before upgrading.

To update units fitted with software older than v1.0.13:

1. Copy the file LanXPLOERER.bin to the root directory of a USB memory key
2. Ensure that the tester is connected to the mains power supply, or that the battery is fully charged
3. Switch the tester ON
4. Insert the USB memory key into the tester
5. Save any results stored in the tester (all data and settings will be lost following the software update) via USB memory key
6. From the HOME screen, select F4(SETUP) / SYSTEM / UPDATE
7. Select F1 (UPDATE)
8. Wait for the update to be completed
9. Update to the current version as described below

To update units fitted with v1.0.13 or later to the current software version (v2.0.42 or later):

1. Copy the file LanXPLOERER-md5.bin to the root directory of a USB memory key
2. Ensure that the tester is connected to the mains power supply, or that the battery is fully charged
3. Switch the tester ON
4. Insert the USB memory key into the tester
5. Save any results stored in the tester (all data and settings will be lost following the software update) via memory key
6. From the HOME screen, select F4(SETUP) / SYSTEM / UPDATE
7. Select F1 (UPDATE)
8. Wait for the update to be completed then
9. Make a factory default reset to select F4(SETUP) / SYSTEM / FACTORY
10. Select F1 (RESET)
11. Wait for the reset to be completed
12. Now the unit ready to use.

To obtain wireless (Wi-Fi) report transfer to mobile devices (smart phone, tablet)

You need to have a dedicated USB Wi-Fi adapter – EdiMax EW-7811UN and download free IDEAL AnyWARE APP (iOS or Andorid) to smartphone or tablet. The existing Internal and External high gain Wi-Fi antenna will not work!!



IDEAL INDUSTRIES LIMITED
Stokenchurch House, Oxford Road, Stokenchurch,
High Wycombe, Bucks, HP14 3SX, UK.

www.idealnetworks.net

A subsidiary of IDEAL INDUSTRIES INC.

