

## Product Description:

Elgar 1751B 260V

## Performance Characteristics of the 1751B

Form Factor	Benchtop
No. of Outputs	1 o/p
Number of Phases	1 ph
Minimum Frequency	45 Hz
Maximum Frequency	5 kHz
Output 1 Max. power	1750 Watts
Number of Ranges	4 QTY
Output 1/Range 1 Max. Current	63.6 Arms (0 Vrms to 32 Vrms)
Output 1/Range 2 Max. Current	31.8 Arms (0 Vrms to 65 Vrms)
Line Regulation, Voltage	0.01625 mV
Load Regulation, Voltage	0.00065 mV
Total Harmonic Distortion	0.56187 dB
RMS Volts Measurement	Yes
RMS Current Measurement	Yes
Frequency Measurement	No
Power Measurement	No
DC Volts Measurement	No
Power Factor Measurement	No
Crest Factor Measurement	No
Overcurrent Protection	Yes
Overvoltage Protection	Yes
Over-temperature Protection	Yes

## Programmability/Connectivity of the 1751B

User Interface Proprietary

## 1751B Life Cycle Data

Out of Production Dec-01-2000

## 1751B Power Requirements

Input Power Universal (Auto Sense and Switch)